

Tyne Rowing Club

Manual for new stopwatches 2013

DIGITAL QUARTZ STOPWATCH

INSTRUCTION MANUAL

Instructions

Introduction

You are about to enjoy an advanced Cumulative and Lap memory professional digital quartz stopwatch with advanced timing features.

Model 998-100M, 998-300M & 998-500M Memory Stopwatch includes Time of day, Daily Alarm, Chronograph stopwatch, 100, 300 or 500 memory, Data register (Model 300M & 500M only), Countdown timer, Stroke Measurement timer, Pacer from 5 to 240 beats per minute.

Model 998-300MDM & 998-500MDM Decimal Stopwatch includes Decimal stopwatch (1/100 of a sec, 1/1000 of a minute, 1/100,000 of an hour).

Model 998-300MSP & 998-500MSP Speed Stopwatch includes Speed Measurement.

General Features

- 4 buttons operation
- Large LCD display with contrast adjustment
- 12/24 hour display
- Normal time and chime
- Daily alarm
- Full 1/100 second chronograph with working range from 0 to 19 hr. 59 min. 59.99 seconds with 100, 300 or 500 memory records of split and lap time.
- Recall function for recorded split and lap times
- Count-Down timer with working range from 0 to 19hr. 59min. 59.9 seconds
- Three operating modes (Countdown Repeat, Countdown Stop, Countdown then count up) for count-down timer
- Stroke measurement basing on "3"
- Speed measurement (SP Model only)
- Decimal second, minute and hour chronograph (DM Model only)
- Segmented run memory (Model 300M & 500M only)
- Beep sound selectable
- Low battery check

As you choose each "mode", a message will be displayed for a second before you enter the mode:

Normal Time mode (All models)	TIME	Timer mode (All models)	TIMER
Alarm Time mode (All models)	ALARM	Pacer mode (All models)	PACER
Chronograph mode (All models)	CHRONO	Stroke Measurement (All models)	STROKE
Lap Time Recall mode (All models)	RECALL	Speed mode (SP model only)	SPEED
Data mode (300M & 500M models only)	DATA		

The operation of the stopwatch is divided into eight modes (as noted above):

1. Normal time mode
2. Alarm time mode
3. Chronograph and Recall mode
4. Data mode (300M & 500M Models only)
5. Count-down timer mode
6. Pacer mode
7. Stroke measurement mode
8. Speed mode (SP model only)

Button Operation

- **Mode** - used to change the mode of the watch
- **Start / Stop / Set** - used to start and stop the timer counting or the chronograph function
- **Recall** - used for recalling recorded split and lap times
- **Lap / Split / Reset / Select** - for taking the record of the split and lap time

This is only a brief description of these buttons. Detailed uses of the buttons are different in particular function and will be described later in the instructions.

Pressing [MODE] button will toggle among the modes above. Note that there is no auto-return function in the stopwatch. Whenever you change modes, the stopwatch will remain in that mode until the [MODE] button is pressed again.

Each time you enter a mode, a message will be displayed for a second before you enter the mode:

Note:- In the following descriptions, items printed in dark gray stand for flashing digits.

Normal Time Mode

The starting point for operating your stopwatch is NORMAL TIME. If NORMAL TIME is not displayed, press [Mode] until it is.

Year : - 2001

Date : - January 1

Day of week : - Monday

Time : - 12:00 am

The display format is as below :-

2001	← year
WE 1 - 3	← day, month - date
A 10:35'30	← hr : min second

During clock display, press [START] to switch between 12Hr and 24Hr display mode. To toggle chime ON or OFF, you can press [RESET]. The bell icon will be ON and OFF correspondingly.

Normal Time Setting

Press and hold [RECALL] for 2 seconds to enter setting mode. The normal time setting starts with second. The second digits will then be flashing. You can change the flashing digit by pressing [START] button. To speed up the setting you can press and hold [START] for longer than 2 seconds to activate fast setting. To select other digits, press [RESET] button. The setting order is: Second, Minute, Hour, Year, Month, Date, month-date (m-d

or date-month (d-m). Sound ON or OFF, Contrast (darkness of the digits - default is 9), then back to the menu and recycles again. Note: when the second is to be set, press [START] to reset the second digits :

At the end of setting, press [RECALL] or [MODE] to exit from the setting mode and back to Normal Display.

Display for Sound ON or OFF setting :-
(Let the current status be "ON")




Press [START] to toggle Sound ON or OFF.



Display for contrast adjustment:-
(Let the current contrast be "5")



Press [START] consecutively to advance the contrast up to 16, then cycle back to 1. The contrast setting will be shown on the display.



NOTE:


- The hour digits may be displayed in 12hr or 24hr format.
- The year digits can be set from 2000 to 2099. The date adjusts automatically for odd and even including February of leap years. The day of week also adjusts automatically after you set the d

4

Alarm Time Mode

Press [MODE] until you enter Alarm mode. This mode is used for displaying the daily alarm time and allows you to enable or disable the alarm.

When you enter the Alarm Time mode, the display shows the alarm time on the upper line while the date is shown in the middle of the display and the normal time is on the lower line.



To toggle the alarm ON or OFF, press [RESET]. When alarm is ON, the indicator "(((o)))" will be ON while it will be turned off when alarm is disabled. When alarm time is reached, the alarm signal will sound for 60 seconds. Press any button to stop the alarm sound.


Setting Alarm Time

Press and hold [RECALL] for 2 seconds to activate the alarm setting. The alarm "minute" digits will flash as an indication. Adjust the flashing digit by pressing [START]. To set the alarm hour digits, press [RESET] to switch to hour digits and then press [START] to adjust. Press [RECALL] or [MODE] to exit from Alarm setting mode.

Chronograph and Recall Mode

Press [MODE] until you enter the Chrono mode.

The stopwatch can measure up to 19 hours, 59 minutes, 59.99 seconds. When you enter the Chronograph mode, the display format is as below.



The upper line shows the split time, the middle line shows the lap time and the accumulated elapsed time is displayed on the lower line.

Whenever the stopwatch stops running, the "STOP" indicator will be ON. Press the button [START/STOP] to start the stopwatch. As it runs, the current elapsed time is shown on the lower line.

{000}	0: 00' 00" 00
SPLIT	0: 00' 00" 00
LAP	
RUN	0: 03' 35" 52

To view the current split / lap time, you can press [LAP/SPLIT].

{001}	0: 10' 43" 35
SPLIT	0: 10' 43" 35
LAP	
RUN	0: 10' 43" 35

The number of split/lap times is shown on the upper left corner. The corresponding split and lap times are displayed on the upper and middle line. Press [LAP/SPLIT] again, the next split/lap time will be shown and the number of split/lap time is updated.

{002}	0: 15' 10" 94
SPLIT	0: 04' 27" 59
LAP	
RUN	0: 15' 10" 94

The stopwatch (Model 500M) can store up to 500 split / lap times. The split/lap times can be stored into the memory as you press [LAP/SPLIT] to view the current split/lap time. Meanwhile, the lap and split time will be frozen for 5 seconds. After this 5-second period, the lap and split time will return to normal.

In addition, the fastest lap, the slowest lap, and the averages of all laps will also be recorded. As you press [STOP] to stop the chronograph, the last lap/split time will also be stored (provided that the last lap/split time is not the first lap/split time).

When there are 5 free memories left, the icon "FULL" will blink to remind you of the nearly full situation. Whenever the storage is full, extra split/lap times will not be stored into memory but will still be shown on the display. Any fastest and slowest laps will not be stored. The memory counter will flash as the extra split/lap times are being displayed. The icon "FULL" will be steadily ON.

6 The maximum memory counter value is 100, 300 or 500.

To stop the chronograph, press [STOP]. The indicator "STOP" will come on again to show the status. Press [RESET] as the stopwatch stops to reset the stopwatch while the split/lap times will be kept in memory. When the stopwatch starts running from reset state, all the lap memories will be cleared.

Decimal Timing (DM model only)

1. The DM Model can operate as a normal 1/100 second chronograph as well as decimal minute, decimal second, and decimal hour chronograph.

As you press [MODE] to enter the chronograph mode, the normal 1/100 second chronograph display will be shown.

{000}	0: 00' 00" 00
SPLIT	0: 00' 00" 00
LAP	
STOP	0: 00' 00" 00

Reset the chronograph to 00, then press [LAP/SPLIT] to go to the second chronograph mode. (1/100s). You will note the change by looking at the bottom of the display to see 1/100s.

{000}	0 0 0 0 0. 0 0
SPLIT	0 0 0 0 0. 0 0
LAP	
STOP	0 0 0 0 0. 0 0
	1/100S

Change to the 1/1000 of a minute chronograph mode by pressing [LAP/SPLIT] again. (1/1000M)

{000}	0 0 0. 0 0 0
SPLIT	0 0 0. 0 0 0
LAP	
STOP	0 0 0. 0 0 0
	1/1000M

Go to the 1/10,000 hour chronograph by pressing [LAP/SPLIT] again.(1/10,000H)

{000}	0. 0 0 0 0 0
SPLIT	0. 0 0 0 0 0
LAP	
STOP	0. 0 0 0 0 0
	1/10000H

Please note that if the stopwatch has started running (or is running), no selection for chronograph operating modes can be made until the stopwatch has been stopped and reset.

Segmented run memory for lap/split time storage:-

A header consisting of the date/time stamp is attached to each segment to indicate the moment when you began recording the particular timing segment. To get to this feature, press [MODE] in chronograph mode to enter DATA mode when the stopwatch has been stopped. Records for different segments can be recalled, read or deleted. Detailed operation in "DATA" mode is described in Data Mode section below.

Chronograph Data Recall Mode

Press [RECALL] in Chronograph mode to recall stored split/lap time memories. The mode message will be shown up for one to two seconds as mode message display is enabled.

RECALL

The split and lap time will be displayed on the upper and the middle line respectively. The lower line shows the current stopwatch counting. During data recall, the fastest lap time will be reviewed first.

RECALL FAST	
{004}	0: 01' 12" 34
SPLIT	0: 00' 01" 60
LAP	
RUN	0: 03' 06" 52

Then comes the slowest lap time by further pressing of [RECALL].

RECALL SLOW	
{001}	0: 00' 07" 63
SPLIT	0: 00' 07" 63
LAP	
RUN	0: 03' 10" 16

8

Press [RECALL] again to view the average lap time.

RECALL AVG	
{005}	
LAP	0: 00' 05" 12
RUN	0: 03' 16" 03

Press [RECALL] continually to review all the stored split/lap times. The sequence starts from the last record to the first record when the stopwatch is running and vice versa when the stopwatch has been stopped.

RECALL	
{005}	0: 00' 14" 91
SPLIT	0: 00' 02" 05
LAP	
RUN	0: 03' 28" 94

[RECALL]

RECALL	
{004}	0: 00' 12" 86
SPLIT	0: 00' 01" 60
LAP	
RUN	0: 03' 33" 64

[RECALL]

RECALL	
{003}	0: 00' 11" 26
SPLIT	0: 00' 01" 78
LAP	
RUN	0: 03' 40" 15

[RECALL]

RECALL	
{002}	0: 00' 09" 48
SPLIT	0: 00' 01" 85
LAP	
RUN	0: 03' 45" 34

9

[RECALL]

RECALL	
{001}	0: 00' 07" 63
SPLIT	0: 00' 07" 63
LAP	
RUN	0: 03' 48" 01

After recalling the first record, press [RECALL] once more to exit from Recall mode and go back to chronograph mode. The "RECALL" icon will be OFF.

[RECALL]

{005}	0: 03' 50" 11
SPLIT	0: 00' 42" 60
LAP	
RUN	0: 03' 50" 11

During memory recall, you can press either [START], [STOP] or [LAP/SPLIT] to exit from chrono recall mode and jump to the chrono start/stop or lap state respectively.

Data Mode (300M & 500M Model only)

Press [MODE] until you enter DATA mode. The mode message "DATA" will be shown for one to two seconds before the number of free memories is to be shown.

FREE
95 LAP

You can press [START] to scroll through all segments. The current segment will come first.

RECALL	
{008}	2 0 0 1
SEG	
{002}	2 - 1 9
A	10: 15' 30

10

The header consisting of the date/time stamp will be shown. The number of laps in the segment will appear in the upper left while the segment number is displayed in the middle left. If the segment shown is not your desired segment, press [START] to reach the desired segment. The current segment will be accessed first, then it will cycle back to the 1st, then 2nd and so on.

When you have found the segment you want, you can press [RECALL] button consecutively to read the lap records from the first to the last lap.

RECALL	
{001}	0: 01' 00" 55
SEG SPLIT	
{002}	0: 00' 12" 86
LAP	
RUN	0: 01' 00" 55

As you continue to press [RECALL] during the display of the last lap, you can advance to the next segment by pressing [START]. The front page of the segment will be shown. Say the next segment is SEG 1.

RECALL	
{012}	2 0 0 1
SEG	
{001}	2 - 1 8
A	10: 00' 15

How to delete individual memory segments:-

Search the desired segment first as described above. During the display of the segment front page, press [RESET] for 2 seconds to activate Delete One function. "DELETE ONE" will be shown in blinking and beep sound will be generated.

d E L E T E
O n E

A "ready" period of 2 seconds will be counted. At the end of the ready period, all the lap records of the corresponding segment will be erased. And a long beep sound will be heard. Then the display will show the next segment. If you don't want to delete the records, you can press any key to exit from delete ready state before the end of the ready period and resume the display of the segment front page.

11

How to delete all memory segments:-

Instead of deleting one segment, you can also delete all memory segments. When you enter the Data mode, you see the screen "FREE XXX LAP". Press and hold the [RESET] for 3 seconds. You will hear "Beep, beep, beep" for 3 seconds, then a long "Beep". At this point all data in the memory will be deleted and "DELETE ALL" will show on the display.

If you don't want to delete the records, you can press any key to exit "DELETE ALL" state before the end of the ready period and resume the display of the segment front page.

```
DELETE
ALL
```

Timer Mode

Press [MODE] until you enter the Timer mode. 3 count-down operation modes are available on this stopwatch:

- Count down repeat (CR)
- Count down stop (CS)
- Count down, then count up (CU)

The timer is set at the factory to the count-down repeat (CR) mode. At entering timer mode, the mode message "TIMER" will be shown for a second before the timer counting is to be displayed.

```
{000} 0: 00' 00" 0
CR 0: 00' 00" 0
A 12 : 58' 20
```

The upper line shows the programmable timer value (initially set at 0:00:00:0) while the middle line displays the current timer counting. Time of Day clock display is at the lower line of the display. "CR" indicates the current timer operating mode while the timer cycle counter is located at the upper left of the display.

Before starting the timer, enter a countdown time first. Then press [START] to start timer running. When the timer counts down to zero, a 3 second "beep ... beep" sound will be generated for a timer setting within one minute; 15 second "beep ... beep" sound for 1 minute to 10 minutes setting and 30 second "beep ... beep" sound for over 10 minutes. Pressing any key will stop the beep sound.

Under CR operation mode, the timer value will be reloaded and count down will start again. The timer cycle counter will be increased by one and updated on the display.

12

Under CS operation mode, the timer, after counting down to 0:00'00"0, will stay at 0:00'00"0 until you press [RESET] to reload the timer value.

Under CU operation mode, the timer, after counting down to 0:00'00"0, will count up and stop at 19:59'59"9.

How to set the timer

Press and hold [RECALL] for 2 seconds to activate timer setting. Timer setting starts with second digits, which are shown blinking. You can press [START] to advance the flashing digits. Or you can press [RESET] to select other digits. The setting is in sequence of second, minute, hour and timer operating mode (CR, CS and CU).

NOTE: You can only set Hour, Minute and Seconds. The 1/10 second cannot be set.

Press and hold [RECALL] for 2 seconds.
Timer setting starts with second digits.

```
{000} 0: 00' 00" 0
CR 0: 00' 00" 0
A 12 : 58' 55
```

Press [RESET] to move to minute digits.

```
{000} 0: 00' 00" 0
CR 0: 00' 00" 0
A 12 : 58' 57
```

Press [RESET] further to go to hour digits. Hour digits can be adjusted from 0 to 19.

```
{000} 0: 00' 00" 0
CR 0: 00' 00" 0
A 12 : 59' 02
```

Press [RESET] again to adjust the operating mode. Press [START] to switch the operating modes among CR, CS and CU.

```
{000} 0: 00' 00" 0
CR 0: 00' 00" 0
A 12 : 59' 11
```

At the end of setting, press [RECALL] or [MODE] to leave setting mode.

Pacer Mode

Press [MODE] until you enter the Pacer mode. In the Pacer mode, you can set the standard pacer speed from 5 to 240 beats per minute in the following values:

5, 10, 20, 30, 40, 50, 60, 80, 100, 120, 150, 180, 200, 240

In Pacer mode, the display will be:-

PACER
P - 5

The digits are flashing to indicate that the pace count is ready for setting. Press [RESET] to select the pace count. Once the desired pace count is selected, press [START] to confirm the setting and start the pace count. The display will show the elapsed time on the upper line, the pace count number on the middle and the pace count value on the lower display.

0: 00' 51" 85
C - 00 51
P - 60

Press [STOP] to stop the pace count. The "STOP" indicator is ON to show the status and the display freezes. To restart the pace count, press [START] again. Or press [RESET] to reset the time elapsed and the pace count number as follows:-

0: 00' 00" 00
C - 00 00
P - 60

Stroke Measurement

Press [MODE] until you enter the Stroke Measurement mode. The display will be as follows.

STROKE
0.0

14

In the Stroke Measurement mode, the duration of 3 strokes is taken and the stroke frequency (counts per minute) is calculated. As the stroke frequency falls out of the range of 10 - 180, "Err" will appear to show the error condition.

Press [START] to start the measurement. During the 1st second, 180.0 will be shown and flashing as below.

STROKE
180.0

At the end of the first second, the display will become steady.

If measurement is stopped in the first second (stroke frequency > 180), error signal "Err" will be shown. After the first second has elapsed, the instantaneous measurement reading will be shown. When you press [STOP], the display will show the steady stroke measurement reading. If the measurement lasts for more than 18 seconds (stroke frequency < 10), an error signal "Err" will be displayed. When the measurement is stopped, press [RESET] to reset the displayed reading to "0.0".

Speed Mode (SP Model only)

Press [MODE] until you enter the Speed mode. The display will be as follows.

{000}	0.000
	0: 00' 00" 00
LAP	0: 00' 00" 00
STOP	0: 00' 00" 00

(Note that the default setting is KM. Hence "KM" icon will be ON.)

The upper line shows the distance or speed. The lap time is in the middle line, while the total time is displayed on the lower line.

In the Speed mode, you can record a number of lap times and speeds for covering the distance you program into the chronograph. Before starting to use the Speed mode, you need to enter the distance as explained below. Otherwise, the speed measurement won't work.

15

Distance Setting

Press [RECALL] for 2 seconds to enter setting mode, the unit icon flashes.

{000}	DIST KM 0 0 0. 0 0 0
LAP	0: 00' 00" 00
STOP	0: 00' 00" 00

Press [START] to toggle between KM and MILE. To select the following digits, press [RESET]. The first digit will blink and you can set the distance from the least significant digit to the most significant digit. Distance can be set in the range 0.000 to 1999.999 km (or ML). Press [RECALL] OR [MODE] to exit from setting mode.

As an example, the distance is set at 400m.

{000}	DIST KM 0. 4 0 0
LAP	0: 00' 00" 00
STOP	0: 00' 00" 00

Speed Mode Running

Press [START] to start the Speed timer. The "STOP" indicator is OFF. The maximum time can be up to 1:59 min. 59.99 sec.

{000}	DIST KM 0. 0 0 0
LAP	0: 00' 00" 00
RUN	0: 00' 05" 35

While the timer is running, press [LAP/SPLIT] to record the lap time and the corresponding speed (in km/h mph) will be displayed on the upper line. The lap counter (shown on the upper left corner) will advance by 0

{001}	DIST KM 2 5. 7 6 0
LAP	0: 01' 05" 35
RUN	0: 01' 05" 35

16

Press [LAP/SPLIT] to record more lap times and show different speeds. Note that as the speed exceeds the value 1999.999 km/hr or 1999.999 mph, "Err" will be shown and no storage will be made for that record.

[LAP/SPLIT]

{002}	DIST KM 2 2. 0 6 0
LAP	0: 01' 05" 25
RUN	0: 02' 01" 15

[LAP/SPLIT]

{003}	DIST KM 2 5. 7 3 0
LAP	0: 00' 55" 95
RUN	0: 02' 57" 10

To stop the speed measurement, press [STOP] to stop the timer.

{003}	DIST KM 2 5. 7 3 0
LAP	0: 00' 59" 13
STOP	0: 03' 48" 23

Before starting again, you can reset the timer by pressing [RESET].

{000}	DIST KM 0. 4 0 0
LAP	0: 00' 00" 00
STOP	0: 00' 00" 00

Note: When you reset the Speed timer, the speed measurement starts again from a reset state, and all speed records in memory will be cleared (provided that the storage is not under segmented run memory mode).

The Recall function is similar to chronograph recall. If segmented run memory is selected, the DATA mode can be accessed and records storing both the speed and elapsed time can be retrieved.

Lap Time & Speed Recall

Similar to the Chrono Recall mode, during speed measurement or Stop state, you can press [RECALL] to recall the speed/lap memories. The Mode message will be shown for one to two seconds as the Mode message display is displayed.

RECALL

The Speed and Lap time will be displayed on the upper and the middle lines. The lower line shows the current time counting. During Data recall, the fastest speed will be reviewed first, then the slowest speed and average speed.

Further presses of [RECALL] will retrieve the memories in ascending order or reverse order depending on whether the speed measurement is stopped or under operation respectively. During Recall, the "Recall" indicator is ON.

(Note: Speed mode and Chrono mode will not run simultaneously. When Chrono mode is active, Speed mode should be in reset state and vice versa.)